



SMC Filter/Regulator Combination, series AW10-40-A

- Modular type filter regulator
- Integrated filter and regulator save space
- Requires less piping
- Optional embedded pressure gauge
- Available with built-in backflow mechanism
- Rc, G(PF) or NPT threads

Characteristics

Series: AW-A

Function: Filter-Regulator

Bowl Material: Polycarbonate

Lockable: No

Operating temperature: -5 / 60 °C

Size	Port thread type	Port Size in	Port Size mm	Filtration level µm	With pressure gauge	Drain type	Flow direction	Self-venting	Adjustment range	Article
										AW40-F04D
40	BSPP (G)	1/2		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04D-A
40	BSPP (G)	1/2		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04D-2-A
40	BSPP (G)	1/2		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04-A
40	BSPP (G)	1/2		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04-2-A
40	BSPP (G)	1/2		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04B-A
40	BSPP (G)	1/2		5	Yes	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04BDG-A
40	BSPP (G)	1/2		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04BG-A
40	BSPP (G)	1/2		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F04G-A
20	BSPP (G)	1/4		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F02C-A
30	BSPP (G)	1/4		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F02D-A
30	BSPP (G)	1/4		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F02-A
20	BSPP (G)	1/4		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F02-C-A
20	BSPP (G)	1/4		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F02-2-A
20	BSPP (G)	1/4		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F02BG-A
20	BSPP (G)	1/4		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F02G-A
20	BSPP (G)	1/8		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F01C-A
20	BSPP (G)	1/8		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW20-F01-A
40	BSPP (G)	3/4		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F06D-A
40	BSPP (G)	3/4		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW40-F06-A
30	BSPP (G)	3/8		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F03D-A
30	BSPP (G)	3/8		5	No	Automatic	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F03C-A
30	BSPP (G)	3/8		5	No	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F03-A
30	BSPP (G)	3/8		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F03BG-A
30	BSPP (G)	3/8		5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW30-F03G-A
10	Metric		M5	5	Yes	Manual	left ? right	Yes	0.05 - 0.7 Mpa	AW10-M5BG-A

Disclaimer: The content of this document has been composed with the utmost care. However, it is possible that certain information changes over time, becomes inaccurate or incomplete. ERIKS does not guarantee that the information provided on this document is up to date, accurate and complete; the information provided is not intended to be advice. ERIKS shall never be liable for damage resulting from the use of the information provided.